

MG 7/5 I-HE



6,1 Lt Fuel Tank



Socket Panel



Honda GX390 Engine



Stage V

We offer now what others will do tomorrow.



Genset s.p.a.

Via Stazione 5 - 27030
Villanova d'Ardenghi (PV) - Italy
Phone: +39-0382-5091

commerciale@genset.it
www.genset.it

 **GenSet**
Next Gen technology
for top business.

PORTABLE POWER GENERATOR
OUTPUT POWER 7,5 kVA THREE-PHASE AND 4 kVA SINGLE-PHASE
PETROL ENGINE 3000 RPM
6,1 LT FUEL TANK

Standard Features	<ul style="list-style-type: none"> • Low oil level shutdown device • 1 x 16 A, 400 V - 50 Hz three-phase EEC socket • 1 x 16 A, 230 V - 50 Hz single-phase EEC socket • Protections for power outputs • Earth Leakage Circuit Breaker (ELCB)
Options available as factory options	<ul style="list-style-type: none"> • Versions with different voltages • 60Hz version • Oversized fuel tank (25 lt) • Automatic voltage regulator (AVR)
Accessories on request	<ul style="list-style-type: none"> • Trolley: two-wheels and handles
Noise level	<ul style="list-style-type: none"> • Lwa 97 (72 dB a 7 mt)
AC generator - 50Hz	<ul style="list-style-type: none"> • Type: synchronous • Three-phase power (max.): 7,5 kVA - 400 V • Single-phase power (max.): 4 kVA - 230 V • Power Factor: $\cos \phi$ 0,8
Petrol Engine 3000 rpm	<ul style="list-style-type: none"> • Type: Honda GX 390 OHV - 1 cyl. - 11 HP (8,2 kWm) - 390 cm³ • Cooling system: air • Starting system: recoil • Fuel tank capacity: 6,1 lt • Fuel consumption @ 75%: 3,3 lt/h
Other features	<ul style="list-style-type: none"> • Insulation Class: H • Ambient temperature: 40 °C (*) • Altitude: 1000 mt (*) • Mechanical Protection: IP 23 • Dimensions (L x W x H): 770 x 480 x 625 mm • Dry weight: 80 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.
 In line with our continued development, innovation and voice of customer program, we reserve the right to change data without notice.