

# **WX 6250 ES**



Pramac portable generators range: prompt power assistance to light up, tackle site jobs and property improvement works. A complete range to choose from, for best solution to your remote power needs. When not fixing up around the job site, your Pramac portable generator can be used for emergency power during a power outage.

#### **FEATURES**

- · OHV engine provides consistent power for multiple applications
- Fuel: Petrol
- Starting Systems: Electric (with battery)
- · Low-oil level shutdown automatically safeguards engine from damage
- Engine oil for the first startup supplied in a bottle
- Digital multi meter tracks engine runtime for maintenance intervals
- Fuel gauge allows user to track gasoline levels
  Pratical quick user's Starting Instruction (decal)
- AVR Automatic Voltage Regulator
- Kit wheels integrated for easy transportation



PERFORMANCE		
Frequency	Hz	50
Voltage	V	400/230
Phase		3
Max Power	Watts	6100
Rated Power	Watts	5500



## Single Phase Power


Voltage	V	230
Single Phase Max Power	Watts	2000
Single Phase Rated Power	Watts	1800

Engine		
Brand		Pramac
Туре		OHV
Exhaust emission level		Stage V
Operating Speed Nominal	rpm	3000
Fuel		Petrol
Starting Systems		Electric (+Recoil)
Oil capacity	1	1.1
Low Oil Shutdown		√



Alternator	
Voltage regulation system	AVR

Dimensional data		
Length	(L) mm	800
Width	(W) mm	698
Height	(H) mm	620
Dry weight	Kg	90
Carton box dimension LxWxH	mm	810x625x607



Autonomy		
Fuel tank capacity		26
Fuel consumption 50%	l/h	2.17
Running time 50%	h	12



Noise level		
Guaranteed noise level (LWA)	dB(A)	97
Noise pressure level @ 7 m	dB(A)	69

## **GENSET CONTROL PANELS**

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.

### **COMMANDS**

• Selector switch: OFF - ON - START

#### **INSTRUMENTATION**

- Voltmeter
- Frequency meter
- Hourmeter
- Fuel gauge

## **PROTECTIONS**

- Thermal protectionOil Guard



SCHUKO 230V 16A IP44	2
3P+N+T CEE 400V 16A IP44	1





