



ENDRESS ESE 606 DHS-GT Single-Phase AVR petrol generator

Reference: 112303

Synchronous current generator with a compact 389 cc. Honda petrol engine, tear-off starter and a large 30 litre tank, which guarantees an autonomy of 13 hours!

ENDRESS ESE 606 HS-GT is equipped with an automatic stop system in case of lack of oil, overload protection, compound.

Suitable for supplying energy to :

- Power tools up to 5400 W
- Gardening tools up to 3600 W
- Compressors or pumps up to 2800 W

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	7.2
Continuous power single phase (KW)	6.4
Maximum power single phase (KVA)	6
Continuous power single phase (KVA)	5.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 2P+T CE - 1 x 230V 32A 2P+T CE
Engine	Honda GX390
Engine rpm (rpm)	3000
Starting system	Manual
Engine capacity (cm ³)	389
Alternator	Synchronous
Poles	2

Nominal current (A)	26.1
Fuel tank capacity (L)	30
Consumption (L/h)	2.2 at 75% of the load
Running time (h)	13 at 75% of the load
Acoustic power	97 dB(A)
Acoustic pressure	72 dB(A) at 7 m
Length (mm)	800
Width (mm)	538
Height (mm)	576
Dry weight (Kg)	73
Silenced	No
Super silenced	No
Voltage regulator	AVR
Engine manufacturer	Honda