



## GENMAC Combipro G5500HC-M5 GENERATOR 5,8KVA

Reference:

### GENMAC COMBIPRO G5500HEC-M5 SINGLE-PHASE GENERATOR 5,8KVA

The generator Genmac Combipro G5500HEC-M5 three phase is equipped with a Honda GX270 Stage V gasoline powered engine capable of delivering a power of 5,8KVA with capacitor voltage regulator (AVR optional).

The Generators of the **Genmac Combipro G5500 series** are among the most **silent** in their category, thanks to the side closing panels and the oversized muffler.

These power generators are built with a **compact and robust** structure with sturdy **wheels and handle** integrated into the frame, which makes them handy and easily transportable. The 300mm diameter wheels with double reinforcement, with which Combipro generators are equipped, are integrated in the structure and the retractable handle can be folded to avoid unnecessary hindrance when not in use. On the frontal part there is also a full length support to avoid sinking into the ground.

The front panel of the Genmac 5,8KVA generator is protected by a canopy and is complete with a back panel that guarantees protection and insulation from water. The generator is equipped with electric starter and injection engine with electronic speed regulation.

The Genmac G5500 5,8KVA generators are equipped with a **25-liter tank** with a large cap that is convenient to unscrew even with work gloves, filter and **fuel level indicator**. There is also a manual fuel circuit shut-off tap to prevent fuel leakage.

The Genmac Combipro mounts a **Honda OHV 4-stroke petrol engine**. They are very reliable engines that guarantee efficient combustion and **low fuel consumption**. The engines with 5,8KVA generators are also equipped with a protection system that causes the **engine to stop if the oil level is too low**.

The Genmac 5,8KVA Generator is equipped with **electronically controlled injection engines** of the GX series.

The 5,8KVA generator with capacitor voltage regulator, on request it can be supplied with AVR.

### AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR voltage regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

### TECHNICAL FEATURES OF GENERATOR GENMAC COMBIPRO G5500HEC-M5

Voltage regulator : capacitor (AVR Optional)  
Power supply: Gasoline  
Firing: Electric  
Phase type: Singlephase / Threephase

Singlephase continuous Output: 1.7KVA / 1.5KW  
 Maximum singlephase Output: 2KVA / 1.8KW  
 Threephase continuous Output: 5.0KVA / 4.0KW  
 Threephase maximum Output: 5,8KVA / 4.6KW  
 Motor: Honda GX270  
 Socket panel: 1 x schuko 230V - 1 x 16A 230V - 1 x 16A 400 V  
 Emission standard: Stage V  
 Voltage: 230 / 400V  
 Frequency: 50 Hz  
 3000 RPM  
 Tank: 25 Lt.  
 Autonomy @ 75%: 15 h fixed RPM  
 Boosting: Manual  
 Length (mm): 800  
 Width (mm): 640  
 Height (mm): 700  
 Dry weight (Kg): 113

If you are looking for another product then you can see on [our catalog](#) other

Images and technical data not binding.

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.8
Continuous power single phase (KW)	1.5
Maximum power single phase (KVA)	2
Continuous power single phase (KVA)	1.7
Maximum power three phase (KW)	4.6
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	5.8
Continuous power three phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO
Engine	HONDA GX270
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	25

---

Running time (h)	
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	
Width (mm)	
Height (mm)	700
Dry weight (Kg)	
Silenced	Yes
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	AVR (optional)
Engine manufacturer	Honda

---