



## DOMETIC T 4000H Petrol Single Phase Generator 3800 Watts 230 V AC

Reference: 9102900006

3,500 watts of direct power to power two air conditioners (e.g. Dometic B 1600PLUS, B 2200, B 3200) or other devices requiring 230 volt alternating current. Powerful petrol engine (9.0 HP).

### Quality characteristics

- Remote Control
- 12 V voltage for battery charger
- Automatic switch-off in case of low oil level
- Electric Ignition
- Electric starter
- Overload and short circuit protection
- Sound absorbing housing
- High continuous power
- Suitable, for example, for operation of two air conditioners

### Dometic B 2200

- Powerful motor
- Remote control for displaying all the parameters of working
- Fueled with unleaded petrol

### Certifications

EC, E3

Non-binding images and technical data.

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.8
Continuous power single phase (KW)	3.5

Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	HONDA GX270
Starting system	Manual / Electric
Cooling	Air
Poles	2
Net power (kW)	6.6
Consumption (L/h)	2.3
Acoustic power	89 dB(A)
Acoustic pressure	62 dB(A) at 7 m
Length (mm)	660
Width (mm)	480
Height (mm)	355
Dry weight (Kg)	102
Silenced	Yes
Super silenced	Yes
Brushes	No
Voltage regulator	No
Engine manufacturer	Honda