



PRAMAC S12000 SINGLE-PHASE Generator set + DPP, AVR

Reference: PD103SH200I

PRAMAC S12000 Single-Phase Generator 10.7 kW DPP AVR

PRAMAC S12000 Single-phase generator, 10.7 kW, with a gasoline engine running at 3000 rpm. The PRAMAC S12000 generator is equipped with an electric starter but also with a recoil starter for manual recoil starting. The alternator of the PRAMAC S12000 generator is equipped with an **AVR** voltage regulator. The Honda petrol engine makes the S12000 DPP AVR generator **very reliable** as it has been built and designed using top-quality materials.

Thanks to its very low weight and **compact dimensions** it is easy to transport where you need it most. The PRAMAC S12000 DPP AVR single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC S12000 Single-phase DPP AVR generator:

Maximum power single-phase: 10.7 KW
Continuous use power single-phase: 9.1 KW
Fuel: Petrol
Voltage: 230 V
Frequency: 50 Hz
Engine: Honda GX630
Starting: Electric
Consumption: 5.63 Lt/h at 100% of load
Length: 960 mm
Width: 641 mm
Height: 667 mm
Weight: 162 kg
AVR

CONTROL PANEL

Controls:

- Ignition key: OFF - ON - START
- Choke button
- Connector (predisposition for remote control via AMF accessories automatic panel; RSS radio remote control)

Instrumentation:

- Voltmeter
- Hour meter

Protections:

- Differential protection
- Circuit breaker protections
- Oil Guard (low oil level)

Sockets:

N.1 SCHUKO 230V 16A IP54
 N.1 2P+T CEE 230V 16A IP44
 N.1 2P+T CEE 230V 32A IP44

The PRAMAC S12000 generator is a professional petrol generator developed by Pramac with the features and equipment necessary to obtain a superior class product. The PRAMAC S12000 generator is characterized by a powerful petrol-powered alternator, protected by a sturdy tubular frame, steel side protection covers, oversized fuel tank, low oil level protection and pre-installed transport kit. The S12000 generator is designed to satisfy long-lasting professional and intensive applications. If you are looking for a generator like the S12000 DPP AVR single-phase generator, we recommend browsing our catalogue of [terrestrial generators](#) to find the one that best suits your needs. Images and data Non-binding technical advice.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	10.7
Continuous power single phase (KW)	9.1
Maximum power single phase (KVA)	11.9
Continuous power single phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	Honda GX630
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico
Oil capacity (L)	1.9
Cooling	Air
Poles	2
Fuel tank capacity (L)	24
Consumption (L/h)	4.23 at 75% of the load / 5.63 at 100% of the load
Running time (h)	5.67 at 75% of the load / 4.26 at 100% of the load
Acoustic power	96 dB(A)
Acoustic pressure	68 dB(A) at 7 m
Length (mm)	960
Width (mm)	641
Height (mm)	667
Dry weight (Kg)	162
Silenced	No
Super silenced	No
Product type	Generator

ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda
