



PRAMAC S8000 SINGLE PHASE AVR

Reference: PD612SH2Z02

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.4
Continuous power single phase (KW)	5.5
Maximum power single phase (KVA)	7.2
Continuous power single phase (KVA)	6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Honda GX390 Electric, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm ³)	389
Oil capacity (L)	1.1
Cooling	Air
Alternator	With brushes

Poles	2
Fuel tank capacity (L)	26.5
Consumption (L/h)	2.15 at 75% of the load / 2.87 at 100% of the load
Running time (h)	12.27 at 75% of the load / 9.23 at 100% of the load
Acoustic power	97 dB(A)
Acoustic pressure	73 dB(A) at 7 m
Length (mm)	840
Width (mm)	
Height (mm)	753
Dry weight (Kg)	109
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda