



PRAMAC ES4000 Single-phase 3.1 KW AVR generator set

Product price:

1,055.22 € tax excluded

Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated. Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase
Maximum power single phase (KW): 3.1
Continuous power single phase (KW): 2.6
Maximum power single phase (KVA): 3.4
Continuous power single phase (KVA): 2.9
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230



Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: Honda GX200, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 196

Oil capacity (L): 0.6

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 1.2 at 75% of the load / 1.6 at 100% of the load

Running time (h): 9.3 at 75% of the load / 7 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 67 dB(A) at 7 m

Length (mm): 623

Width (mm): 409

Height (mm): 500

Dry weight (Kg): 43

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda

