



PRAMAC ES5000 SINGLE PHASE AVR

Product price:

1.554,75 € tax excluded

Product description:

Gasoline model developed by Pramac to guarantee a high level of quality and performance at an attractive price.

Generator ideal for intense applications, characterized by a sturdy structure with tubular supporting frame that simplifies both its use and maintenance operations.

The essential tool to satisfy professional applications.

HONDA GX series petrol engines

Air cooling

Oil Guard protection

Tear-off starter

Synchronous alternators available with AVR

? Sturdy structure with tubular supporting frame

Sockets on headphones with thermal protection.

? Oversized tanks (11 litres)

? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.6

Continuous power single phase (KW): 3.9

Maximum power single phase (KVA): 5.1

Continuous power single phase (KVA): 4.2

Fuel: Gasoline

Frequency (Hz): 50



Voltage (V): 230

Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44

Engine: Honda GX270 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 1.6 at 75% of the load / 2.2 at 100% of the load

Running time (h): 6.6 at 75% of the load / 5 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 729

Width (mm): 500

Height (mm): 536

Dry weight (Kg): 61

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda

