



## LINZ E1E13M E Single-phase alternator 115V/230V 18 kVA 50 Hz AVR

Reference: E1E13M E 50 Hz J609b

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

### CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE  
product available 50 Hz and 60 Hz

Images and technical data are not binding.

### Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	18
Continuous power single phase (KVA)	18
Frequency (Hz)	50 / 60
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	18
Protection degree	IP21
Motor insulation class	H

---

Length (mm)	495
Width (mm)	270
Height (mm)	379
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	89

---