



LINZ E1X13M D/2 Three-phase alternator 230V/400V 16 kVA 50 Hz 60 Hz AVR

Reference: E1X13M D/2 50 Hz J609b

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
 - Minimum maintenance
 - High efficiency
 - Type: Three-phase alternators
 - Poles: 2
 - Phases: Three-phase
 - Regulation: AVR
 - Application: PORTABLE, TELECOMMUNICATION
- Product available in 50 Hz and 60 Hz versions

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	12.8
Continuous power three phase (KVA)	16
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Three-phase power (KVA)	16
Protection degree	IP21

Motor insulation class	H
Length (mm)	554
Width (mm)	270
Height (mm)	375
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	86
