



## LINZ E1X13M E/2 Three-phase alternator 230V/400V 22 kVA 50 Hz AVR

Reference: E1X13M E/2 50 Hz J609b

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

### CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION  
product available in 50 Hz and 60 Hz versions

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	17.6
Continuous power three phase (KVA)	22
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Three-phase power (KVA)	22
Protection degree	IP21

---

Motor insulation class	H
Length (mm)	554
Width (mm)	270
Height (mm)	375
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	97

---