



GENMAC DAILY RG7300HS-M5 GENERATOR 7,1KVA

Reference:

GENMAC DAILY RG7300HS-M5 SINGLE-PHASE GENERATOR 7,1KVA

The **generator** Genmac Daily RG7300HS-M5 single-phase is equipped with a gasoline powered **Honda** engine capable of delivering a power of **7,1KVA** with capacitor voltage regulator (AVR optional).

Genmac's high quality professional silenced single-phase gasoline generator with 7,1KVA power. The Genmac gasoline power generator is equipped with an oversized air-cooled Honda engine.

Genmac professional gasoline generators are highly reliable machines, built with quality components to be used in professional field, where reliability is fundamental.

This feature is fundamental to guarantee a high reliability of the generator, reduces its effort and increases its life span by lowering the noise level.

All Honda engines are built using the best materials, the most innovative techniques and the most advanced methods for quality control.

The 7,1KVA generator is equipped with a capacitor voltage regulator, on request it can be supplied with the **AVR regulator**.

AVR Voltage Regulator

All Genmac series models are available with optional AVR voltage regulator. The AVR is a device that allows to keep the output more constant and less dependent on the load. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving performance and durability.

The model equipped with AVR board is highly recommended, as it guarantees a significant improvement in the stability of the output; this feature makes the generators particularly suitable for common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you will enjoy greater stability and therefore an increase in the life of your devices.

TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Daily RG7300HS-M5 7,1KVA

Power supply: Gasoline
Continuous power PRP: 6.4KVA / 5.8KW
Standby power LTP: 7.1KVA / 6.4KW
Power factor cos ϕ ?: 0.8
Phase Type: Single Phase
VAC Voltage: 230 V
Frequency (Hz): 50
Voltage Regulator: Compound (AVR Optional)

ATS Panel: standard setup (Panel Optional)
 Motor: HONDA iGX390
 Socket Panel: 1 x 16A 230V / 2 x 32A 230V
 Emissions Standard: STAGE 5
 Tank capacity: 19 l
 Autonomy at 75% load: 11 h
 RPM: 3000
 Sound pressure: 63 dB(A) @ 7 m
 Length (mm): 1030
 Width (mm) 620
 Height (mm) 804
 Net weight (kg): 193

If you are looking for another product then you can consult other terrestrial generators in [our catalog](#).

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.4
Continuous power single phase (KW)	5.8
Maximum power single phase (KVA)	7.1
Continuous power single phase (KVA)	6.4
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Honda iGX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	19
Running time (h)	11 at 75% of the load
Acoustic pressure	63 dB(A) a 7 m
Length (mm)	
Width (mm)	620
Height (mm)	

Dry weight (Kg)	193
Silenced	Yes
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	AVR (optional)
Engine manufacturer	Honda
