



VISA CK 9 GENERATOR SET SILENCED 9 KVA AVR

Reference: P 9 CK

GENERATOR VISA CK9

VISA CK9 is a silenced overland generator set, with 9KVA power in continuous use and AVR, mounts components of primary brand: the CK9 model uses a reliable PERKINS 403A-11G1 diesel engine with 3 cylinders, 1500 rpm and a STAMFORD PI044E alternator equipped with AVR AS480 with a voltage regulation accuracy of 1%.

The **VISA CRICKET** industrial power generators feature silenced enclosures and tropicalized treatment, making them suitable for use in hot climates; in particular the VISA CK 9 is water-cooled, which ensures excellent heat management.

The robust chassis of the VISA CK9 contains a capacious 55-liter fuel tank, which gives it an autonomy of more than 27 hours at 75% load; moreover the dimensions of this generator are optimized for its transport by truck and its storage on a 40' HC container.

The VISA CK9 is also suitable for use in hot climates.

Most important advantages of choosing a Visa CK9 industrial generator

- 1 - Original industrial diesel engine with certificate of origin
- 2 - Brushless industrial alternator with AVR
- 3 - Steel basement, tank with electrolevel
- 4 - Soundproof hood completely in galvanized sheet metal and painted with polyester powders
- 5 - Soundproofing material in polyester fiber with high abatement
- 6 - Residential exhaust silencer with insulated manifold
- 7 - Electrical panel mounted on board the machine with control device and protection device integrated in the box
- 8 - Compactness for ease of handling and use
- 9 - Test certification, manuals and diagrams included
- 10 - World wide after-sales technical assistance support
- 11 - CRICKET RANGE: FROM 9 TO 200kVA at 50 or 60Hz.

Automatic control box AMF

- 1 - On/off key;
- 2 - Emergency stop button;
- 3 - DEEP SEA® 4520 MKII;
- 4 - Main switch of primary brand .

DEEP SEA® 4520 MKII

DSE4520 control panel is a compact automatic power failure control module. By monitoring a large number of generator parameters, the module is able to display warning, shutdown and engine status information on the backlit LCD display.

This control panel allows the CK9 generator to be paired with a [genset/genset switching](#) for automatic starting.
 Accessories available:

- Engine pre-heating system;
- Genset/genset switching board

Pictures and non-binding technical data

Technical Sheet

Phase	Three phase
Maximum power three phase (KW)	8
Continuous power three phase (KW)	7.2
Maximum power three phase (KVA)	10
Continuous power three phase (KVA)	9
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	400
Sockets configuration	Terminal box
Engine	Perkins 403A-11G1
Emissions Regulations	Stationary Use
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Electric
Engine capacity (cm ³)	1131
Number cylinders	3
Oil capacity (L)	4.9
Cooling	Water
Poles	4
Three-phase power (KVA)	10
Fuel tank capacity (L)	55
Consumption (L/h)	2 at 75% of the load
Running time (h)	27.7
Length (mm)	1575
Width (mm)	745
Height (mm)	1270
Dry weight (Kg)	515
Silenced	Yes

Brushes	No
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Perkins
Precision of voltage regulation	± 1%
