



CGM C7000 SINGLE PHASE GENERATOR 7KVA

Reference: CGM C7000

GENERATOR CGM C7000 SINGLE-PHASE 7 KVA

The Generator CGM C7000 single-phase 7 KVA with Honda engine powered by gasoline STAGE V at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The generator is composed of a Made in Italy Linz or NSM alternator, self-excited without brushes and with AVR voltage regulator.

The CGM C7000 generator is equipped with a manual recoil starter but it is also available in the version with electric start and with a low fuel consumption, in fact it consumes only 2 liters/hour at 75% of the load.

This CGM C7000 generator is perfect for outdoor use such as for hobbyist use. The CGM C7000 genset is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, camping, hobbies, construction sites, etc.

The CGM generator set at 3000 rpm is suitable for emergency use only. It is not recommended for use for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM C7000 generator:

Phase type: Single phase
Maximum power: 6.9 KW
Continuous power: 6.3 KW
Maximum power: 7.7 KVA
Continuous power: 7 KVA
Fuel: Gasoline
Voltage: 230 V
Frequency: 50 Hz
Engine: HONDA GX390
Engine RPM: 3000 RPM
Start: Manual
Voltage regulator system: AVR
Consumption: 2 Lt/h at 75% load
Tank capacity: 6.1 Lt
Autonomy: 3 h at 75% load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 75 Kg

Discover the full range reserved for [Generator](#) of CGM or other of the best brands browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

| | |
|-------------------------------------|---|
| Phase | Single phase |
| Maximum power single phase (KW) | 6.9 |
| Continuous power single phase (KW) | 6.3 |
| Maximum power single phase (KVA) | 7.7 |
| Continuous power single phase (KVA) | 7 |
| Fuel | Gasoline |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 |
| Sockets configuration | 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE |
| Engine | Honda GX390 |
| Emissions Regulations | Stage 5 |
| Engine rpm (rpm) | 3000 |
| Starting system | Manual |
| Engine capacity (cm ³) | 389 |
| Number cylinders | 1 |
| Alternator | Made in Italy |
| Poles | 2 |
| Fuel tank capacity (L) | 6.1 |
| Consumption (L/h) | 2 |
| Running time (h) | 3 |
| Length (mm) | 780 |
| Width (mm) | 510 |
| Height (mm) | 500 |
| Dry weight (Kg) | 75 |
| Silenced | No |
| Super silenced | No |
| Product type | Generator |

| | |
|---------------------|--------|
| ATS Switch device | No ATS |
| Voltage regulator | AVR |
| Engine manufacturer | Honda |
