



CGM C5000T

Reference: CGM C5000T

Generator CGM C5000T Three-phase 5 KVA

CGM C5000T three phase 5 KVA generator set with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers. The CGM C5000T generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C5000T generator set is equipped with manual recoil starter with recoil starter and low fuel consumption, in fact it consumes only 1.6 litres/hour at 75% of the load. This C5000T generator set is perfect for outdoor use such as hobby use.

The CGM C5000T is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, street installations, camping sites, hobbies, construction sites, etc.. The C5000T generator set at 3000 rpm is only suitable for emergency use. We do not recommend use for more than 6 consecutive hours and more than 500 hours per year.

Technical characteristics of the CGM C5000T:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 1.85 KVA / 1.6 KW

Continuous singlephase power: 1.7 KVA / 1.3 KW

Maximum threephase power: 5.5 KVA / 4.8 KW

Continuous threephase power: 5 KVA / 4 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: HONDA GX270

Engine rpm: 3000 rpm & It;

Starting: Manual

Voltage regulator system: AVR

Consumption: 1.6 Lt / h at 75% of load

Tank capacity : 5.3 Lt

Autonomy: 3.3 h at 75% of the load

Length: 780 mm

Width: 510 mm

Height: 500 mm

Weight: 58 Kg

Discover the full range of [generators](#) from CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.6
Continuous power single phase (KW)	1.3
Maximum power single phase (KVA)	1.8
Continuous power single phase (KVA)	1.7
Maximum power three phase (KW)	4.8
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	
Continuous power three phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine	HONDA GX270
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm ³)	270
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	5.3
Consumption (L/h)	1.6
Running time (h)	25
Length (mm)	780
Width (mm)	
Height (mm)	500
Dry weight (Kg)	58
Silenced	No

Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda
