



CGM C7000T

Reference: CGM C7000T

Generator CGM C7000T Three-phase 7 KVA

CGM C7000T single/threephase 7 KVA generator set with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C7000T generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C7000T generator set is equipped with manual recoil starter with recoil starter and low fuel consumption, in fact it consumes only 2 litres/hour at 75% of the load. This CGM C7000T generator set is perfect for outdoor use such as hobby use.

The CGM C7000T generator set is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, street installations, camping sites, hobbies, construction sites, etc.. The CGM C7000T at 3000 rpm is only suitable for emergency use. We do not recommend use for more than 6 consecutive hours and more than 500 hours per year.

Technical characteristics of the CGM C7000T:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 2.6 KVA / 2 KW
Continuous singlephase power: 2.3 KVA / 1.8 KW
Maximum threephase power: 7.7 KVA / 6.1 KW
Continuous threephase power: 7 KVA / 5.6 KW
Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Motor: HONDA GX390
Engine rpm: 3000 rpm
Starting: Manual
Voltage regulator system: AVR
Consumption: 2 Lt / h at 75% of the load
Tank capacity: 6.1 Lt
Autonomy: 3 h at 75% of the load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 75 Kg

Discover the full range of [generators](#) from CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	1.8
Maximum power single phase (KVA)	2.6
Continuous power single phase (KVA)	2.3
Maximum power three phase (KW)	6.1
Continuous power three phase (KW)	5.6
Maximum power three phase (KVA)	7.7
Continuous power three phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm ³)	389
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2
Running time (h)	3
Length (mm)	780
Width (mm)	
Height (mm)	500
Dry weight (Kg)	75
Silenced	No
Super silenced	No

Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda
