



CGM C11000T

Reference: CGM C11000T

CGM C11000T Three-phase generator 10 KVA

CGM C11000T Three-phase generator 10 KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C11000T is composed of a Made in Italy alternator by Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C11000T generator set is equipped with manual recoil start and with a low fuel consumption, in fact it consumes only 2,2 liters/hour at 75% of the load for an autonomy up to 3 hours of operation. This generating set CGM C11000T is perfect for outdoor use as for example for hobby use.

The CGM C11000T is part of the CLASSIC series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites etc.. The CGM C11000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical features of CGM C11000T:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 3.6 KVA / 3 KW
Continuous singlephase power: 3.3 KVA / 2.6 KW
Maximum threephase power: 11 KVA / 8.8 KW
Continuous threephase power: 10 KVA / 8 KW
Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Motor: BRIGGS & STRATTON 16HP
; Engine revolutions: 3000 rpm
Starting: Manual
Voltage regulator system: AVR
Consumption: 3.8 Lt / h at 75% of the load
Capacity tank: 8.5 Lt
Autonomy: 2.2 h at 75% of the load
Length: 910 mm
Width: 580 mm
Height: 640 mm
Weight: 97 Kg

Discover the full range reserved for [generator](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	
Continuous power single phase (KVA)	3.3
Maximum power three phase (KW)	8.8
Continuous power three phase (KW)	8
Maximum power three phase (KVA)	11
Continuous power three phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine	Briggs&Stratton
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm ³)	480
Number cylinders	2
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	
Consumption (L/h)	3.8
Running time (h)	2.2
Length (mm)	910
Width (mm)	580
Height (mm)	64

Dry weight (Kg)	97
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Briggs&Stratton
