



CGM CX7000TE

Reference: CGM CX7000TE

Generator CGM CX7000TE Three-phase 7KVA AVR

Generator CGM CX7000TE Three phase 7KVA with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers. The CGM CX7000TE generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM CX7000TE generator set is equipped with electric starter and low fuel consumption, in fact it consumes only 2 litres/hour at 75% of the load. This CX7000TE generator set is perfect for outdoor use such as hobby use.

The CGM CX7000TE generator set is part of the DELUXE series and is easily adaptable to a variety of uses such as homes, street installations, camping, hobbies, construction sites, etc.. The CX7000TE generator set at 3000 rpm is only suitable for emergency use. It is not recommended to use it for more than 6 hours continuously and for more than 500 hours per year.

Technical characteristics of the CGM CX7000TE generator:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 2.5 KVA / 2 KW
Continuous singlephase power: 2.3 KVA / 1.8 KW
Maximum threephase power: 7.7 KVA / 6.1 KW
Continuous threephase power: 7 KVA / 5.6 KW
Fuel: Petrol
Voltage: 230 V / 400 V
Frequency: 50 Hz
Engine: HONDA GX390
Engine revs: 3000 rpm
Starting: Electric
Voltage regulator system: AVR
Consumption: 2 Lt/h at 75% of the load
Tank capacity: 15 Lt
Autonomy: 7.5 h at 75% of the load
Length: 825 mm
Width: 550 mm
Height: 530 mm
Weight: 85 Kg

Discover the entire range reserved for [generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	1.8
Maximum power single phase (KVA)	2.5
Continuous power single phase (KVA)	2.3
Maximum power three phase (KW)	6.1
Continuous power three phase (KW)	5.6
Maximum power three phase (KVA)	7.7
Continuous power three phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm ³)	389
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	15
Consumption (L/h)	2
Running time (h)	7.5
Length (mm)	825
Width (mm)	550
Height (mm)	530
Dry weight (Kg)	85
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	Optional ATS

Voltage regulator	AVR
Engine manufacturer	Honda
