



GENERATOR RENTAL 12KVA AVR

Reference: SE12000-MTHE NOLEGGIO

GENERATOR RENTAL 12KVA AVR SET WFM SE12000-MTHE ELECTRIC GROUP

Generator Rental 12KVA WFM SE12000-MTHE singlephase / threephase generator set equipped with Honda GX690R gasoline engine capable of delivering a maximum power of 12KVA, complete with AVR **voltage regulator**.

Generator Rental 12KVA AVR WFM SE12000-MTHE is a generator set equipped with a protection cabin that makes it super silenced, equipped with electric start, single-phase output of 4KVA and three-phase output of 12 KVA.

RENTAL SERVICE

Generator 12KVA has never been easier: choose the product you want to rent and [FILL OUT THE FORM](#).

Our specialized staff will respond immediately with the offer that best suits you!

The equipment available for rental can be shipped throughout Italy and is always ready for action: our team of technicians will always keep it in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will be using the rental service.

Voltage Regulator AVR

The Generator 12KVA AVR WFM SE12000-MTHE is equipped with an AVR. The AVR is a device that allows you to **keep the output more constant and less dependent on the load**. Thanks to this card there are fewer drops or spikes in current and this makes it safer to use the various devices connected, improving performance and durability.

Main Features of Generator Rental 12KVA AVR WFM SE12000-MTHE:

- Soundproof protection frame
- Original Honda or Lombardini engine
- Low oil level protection
- Silencer muffler
- Primary Italian brand alternator
- Electric start with 12V battery
- Full load test with test certificate

TECHNICAL FEATURES WFM SE12000-MTHE

Phase Type: Single-phase / Three-phase

Continuous Singlephase Power: 3.3 KVA / 2.6 KW
 Maximum Singlephase Power: 4 KVA / 3.2 KW
 Continuous Threephase Power: 10 KVA / 8 KW
 Maximum Threephase Power: 12 KVA / 9.6 KW
 Factor cos fi?: 0.8
 VAC voltage: 230 / 400 V
 Frequency (Hz): 50
 Voltage regulator: AVR
 Start-up switch: manual
 Motor: Honda GX690R
 RPM: 3000
 Supply: Gasoline
 Tank capacity: 20 l
 Consumption: 4.6 l/h @ 100 % of load
 Autonomy: 4.34 h @ 100 % of load
 Acoustic pressure: 67 @ 7m
 Length: 1070 mm
 Width: 563 mm
 Height: 921 mm
 Net weight: 210 Kg

Are you looking to rental a generator set with different technical characteristics? [Here](#) you can find our entire rental fleet where you can find the perfect generator for you.

Available for Turin and all of Italy.

Images are for guidance only.

""

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3.2
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	4
Continuous power single phase (KVA)	3.3
Maximum power three phase (KW)	9.6
Continuous power three phase (KW)	8
Maximum power three phase (KVA)	12
Continuous power three phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 CEE 5P 400V 16A + 1 CEE 3P 230V 16A
Engine	Honda GX690

Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	688
Number cylinders	2
Oil capacity (L)	1.9
Cooling	Air
Fuel tank capacity (L)	20
Consumption (L/h)	4.6 at 100% of the load
Running time (h)	4.34 at 100% of the load
Acoustic power	92 dB(A)
Acoustic pressure	67 dB(A)
Length (mm)	1070
Width (mm)	563
Height (mm)	921
Dry weight (Kg)	210
Silenced	Yes
Super silenced	Yes
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Honda