



## GENMAC Combiplus G15000HEO-E5 GENERATOR StageV 15,3KVA

Reference:

### GENMAC Combiplus G15000HEO-E5 GENERATOR 15,3KVA StageV

The **generator Genmac Combiplus G15000HEO-E5** Single Phase / Three Phase has a Honda gasoline powered engine capable of delivering a power of 15,3KVA with the possibility of connection to optional AVR.

The GENMAC Combiplus G15000HEO-E5 generator is equipped with a Honda Stage V engine certified for mobile use in the EU, but which does not comply with others criteria of the regulation. The engine is powered by gasoline by means of a tank with a capacity of 19 liters for an autonomy of about three and a half hours, complete with electric starter.

The Genmac 15,3KVA generator is equipped with a front control panel for portable units, with manual start and oil level sensor, with the possibility of modification by the customer with the optional remote control panel.

In combination with the generator it is possible to request the handling kit specifically designed for the selected model, for a more comfortable transport before the installation on the working lug.

The 15,3KVA generator is equipped with compound voltage regulator, on request it is possible to supply it with AVR voltage regulator.

#### Optional AVR regulator

The AVR brings a significant improvement in output voltage stability; this is particularly useful with commonly used machines with reactive load, such as refrigerators, freezers, air conditioners and garden machines. This will increase the life of your devices.

The optional AVR is a device that keeps the out voltage more constant and less load-dependent. Thanks to this technology there are fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

Technical features of generator 15,3KVA Genmac Combiplus G15000HEO-E5

Power Supply: Gasoline

Firing: Electric

Phase Type: SinglePhase / ThreePhase

Continuous SinglePhase output: 4.6 KVA / 4.1 KW

Maximum SinglePhase output: 5.1 KVA / 4.6 KW

Threephase continuous output: 13.8KVA / 11.0KW

Threephase maximum output: 15.3KVA / 12.2KW

Motor: Honda GX690

Socket panel: 1 x 16A 230V - 1 x 32 A 400 V

Voltage: 230 / 400V

Frequency: 50 Hz

3000 rpm  
Tank: 19 Lt.  
Autonomy @ 75%: 4,2 h fixed revolutions  
Starting: Manual  
Length (mm): 870  
Width (mm): 620  
Height (mm): 690  
Dry weight (Kg): 166

Emissions standard: Stage V

If you are looking for another product then you can consult on [our catalog](#) other generator.

Images and technical data are not binding and may be subject to review

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	4.6
Continuous power single phase (KW)	4.1
Maximum power single phase (KVA)	5.1
Continuous power single phase (KVA)	4.6
Maximum power three phase (KW)	12.2
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	15.3
Continuous power three phase (KVA)	13.8
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine	
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Fuel tank capacity (L)	19
Running time (h)	4.2
Length (mm)	870
Width (mm)	620
Height (mm)	690

---

Dry weight (Kg)	166
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR (optional)

---