



GENMAC Combipro G5500HAC-M5 GENERATOR 5,8KVA

Reference:

GENMAC COMBIPRO G5500HAC-M5 THREE-PHASE GENERATOR 5,8KVA

The generator Genmac Combipro G5500HAC-M5 Three phase is equipped with a Honda STAGE V gasoline powered engine capable of delivering a power of **5,8KVA with** capacitor voltage regulator (AVR optional).

The Generators of the **Genmac Combipro G5500 series** are among the most **silent** in their category, thanks to the side closing panels and the oversized muffler. The panels are covered with a **silent** silent material in polyester, this material is recyclable, washable, class 1, fire retardant and self-extinguishing.

These power generators are built with a **compact and robust** structure with sturdy **wheels and handle** integrated into the frame, which makes them handy and easily transportable.

The front panel of the Genmac 5,8KVA generator is protected by a canopy and is complete with a back panel that guarantees protection and insulation from water. The generator is equipped with electric starter and injection engine with electronic speed regulation.

The Genmac G5500 5,8KVA generators are equipped with a **25-liter tank** with a large cap that is convenient to unscrew even with work gloves, filter and **fuel level indicator**. There is also a manual fuel circuit shut-off tap to prevent fuel leakage.

Genmac Combipro generators are equipped with an iGX series Honda fuel-injected engine with electronic speed control, ensuring efficient combustion and low fuel consumption. The engines in the 5.8KVA generators are also equipped with a protection system that causes the engine to stop if the oil level is too low.

The 5,8KVA generator is equipped with capacitor voltage regulator, on request it is possible to supply it with AVR regulator.

TECHNICAL FEATURES OF GENERATOR GENMAC COMBIPRO G5500HAC-M5

Voltage regulator : capacitor (AVR Optional)
Power supply: Gasoline
Firing: Electric
Phase type: Singlephase / Threephase
Singlephase continuous output: 1.7KVA / 1.5KW
Maximum singlephase output: 2KVA / 1.7KW
Threephase continuous output: 5.0KVA / 4.0KW
Threephase maximum output: 5.8KVA / 4.6KW
Motor: Honda iGX270
Socket panel: 1 x schuko 230V - 1 x 16A 230V - 1 x 16A 400 V
Emission standard: Stage V
Voltage: 230 / 400V
Frequency: 50 Hz

3000 revolutions per minute
Tank: 25 Lt.
Autonomy @ 75%: 18 h fixed revolutions
Starting: Manual
Length (mm): 800
Width (mm): 640
Height (mm): 700
Dry weight (Kg): 115

If you are looking for another product then you can see on [our catalog](#) other generator

Images and technical data not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.7
Continuous power single phase (KW)	1.5
Maximum power single phase (KVA)	2
Continuous power single phase (KVA)	1.7
Maximum power three phase (KW)	4.6
Continuous power three phase (KW)	4
Maximum power three phase (KVA)	5.8
Continuous power three phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO
Engine	Honda iGX270, 4 stroke, OHV
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	25
Running time (h)	18
Acoustic pressure	69 dB(A) at 7 m
Length (mm)	
Width (mm)	
Height (mm)	700

Dry weight (Kg)

Silenced

Yes

Super silenced

No

ATS Switch device

ATS Included

Voltage regulator

AVR (optional)

Engine manufacturer

Honda
