



## GENMAC Living RG7KS-M5 GENERATOR 7,2KVA

Reference: Living RG7KS-M5

### GENMAC LIVING RG7KS-M5 SINGLE-PHASE GENERATOR 7,2KVA

The GENMAC Living RG7KS-M5 single-phase generator features a diesel-powered Kohler stage V engine capable of delivering 7,2KVA with AVR regulator.

The GENMAC Living RG7KS-M5 generator features a liquid-cooled, three-cylinder, horizontal-shaft engine, aluminum head and multiple PTO points ensure maximum performance.

GENMAC Living RG7KS-M5 are highly reliable machines, built with quality components for use in the professional field, where reliability is paramount.

The Stage V engine also allows the generator set to be used for mobile use, such as for road construction sites and rental services. The GENMAC Living RG7KS-M5 is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

The diesel engine maintains the standard engineering performance you've come to expect from Kohler. An advanced fuel injection system uses fuel more efficiently, while high-efficiency combustion significantly reduces emissions.

The GENMAC features a soundproof cabin that allows noise propagation of no more than 68 dB (A) at 7 m, this feature makes it suersilenced.

#### Voltage Regulator AVR

The voltage regulator is indispensable to make the generator work at its best, in fact it needs an electronic control system, an AVR, which guarantees the good working of the machine and of the electric network underneath it.

The purpose of the AVR, in a current generator, is to maintain a stable output. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed current opposes the inductor magnetic field, causing a voltage drop at the alternator output terminals; to compensate the phenomenon, the regulator intervenes automatically increasing the excitation current, until the output returns to the nominal value. If the load is capacitive, the current magnetizes the inductor causing an increase in the output voltage, and the AVR intervenes by reducing the excitation current

#### TECHNICAL FEATURES GENMAC Living RG7KS-M5 7.2KVA

Phase Type: Single Phase  
Continuous Power: 6.9KVA / 6.2KW  
Maximum Power: 7.2KVA / 6.5KW  
Motor: Kohler KDW1003  
Emission Standard: Stage V  
Start: Electric

Power supply: Diesel  
 Socket panel: 1 x Schuko 16A 230V - 1 x 32A 230V - 1 x 63A 230V  
 Voltage: 230V  
 Frequency: 50 Hz  
 Motor speed: 1500 rpm  
 Tank capacity: 76 l  
 Autonomy @ 75%: 38 h fixed rpm  
 Voltage regulator : AVR  
 Acoustic pressure @7m: 61 dBa  
 Length (mm): 1056  
 Width (mm): 590  
 Height (mm): 1442  
 Dry weight (Kg): 385

If you are looking for another product then you can see on our catalog other [ground generators](#).

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.5
Continuous power single phase (KW)	6.2
Maximum power single phase (KVA)	7.2
Continuous power single phase (KVA)	
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 63A 2P+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V 16A 2P+T CEE
Engine	KOHLER KDW1003
Emissions Regulations	Stage 5
Engine rpm (rpm)	1500
Starting system	Elettrico
Cooling	Water
Poles	2
Fuel tank capacity (L)	
Running time (h)	38
Acoustic pressure	61 dB(A) at 7 m
Length (mm)	
Width (mm)	590

---

Height (mm)

---

Dry weight (Kg)

---

Silenced	Yes
----------	-----

---

Super silenced	Yes
----------------	-----

---

ATS Switch device	Optional ATS
-------------------	--------------

---

Voltage regulator	AVR
-------------------	-----

---

Engine manufacturer	Kohler
---------------------	--------

---