



MECC ALTE ECP28-1L/2 C-TYPE THREE-PHASE ALTERNATOR 25KVA

Reference: ECP28-1L/2 C-TYPE

MECC ALTE ECP28-1L/2 C-TYPE ALTERNATOR 25KVA THREEPHASE

Alternator MECC ALTE ECP28-1L/2 C-TYPE with a power of 25KVA, this unit has a Brushless self-exciting and self-regulating operation equipped with **DSR** voltage regulator.

The ECP28-1L/2 C-TYPE alternator is designed to operate at 50 or 60 HZ frequency, the possibility of working on these two frequencies makes it possible to apply it for any service voltage increasing its versatility, for the correct operation.

The ECP28-1L/2 alternators mount button-type diodes, mounted directly in the exciter's diode holder, or mounted on a detachable diode bridge, divided into three sectors. In the case of the bridge, each single diode can be checked very easily with a multimeter specially set for diode checking; disconnect the three sectors completely and check each diode in both directions. In case of one or more faults, it is advisable to replace the complete bridge.

MECC ALTE ECP28-1L/2 C-TYPE is supplied with 12 terminals (7 clamps), with which it is normally possible to connect the alternator both in series star and parallel star. According to the needs it is possible to pass from a connection to another one keeping in mind that it is necessary to verify the DSR connection.

ECP28-1L/2 C-TYPE can be used as singlephase depending on the needs. MECC ALTE ECP28-1L/2 is equipped with digital current regulator DSR . The regulator is suitable for operation on both threephase and singlephase generators, allowing fast, accurate and reliable tuning.

All MECC ALTE ECP28 alternators have the MAUX auxiliary winding to power the DSR digital regulator. You can connect the DSR voltage regulator to your PC via the DxR2 USB interface and DxR TERMINAL software to query/download alarms and settings for analysis.

Select the alternator that reflects the **technical specifications you require**, visit our [dedicated section](#) to find out how.

TECHNICAL FEATURES OF 22KVA MECC ALTERNATOR ECP28-1L/2 C-TYPE

Phase Type: Singlephase / Threephase
Maximum threephase power: 24KW
Threephase continuous power: 20KW
Maximum threephase power: 30KVA
Threephase continuous power: 25KVA
Frequency: 50 / 60 Hz
Voltage: 230 / 400 V
Protection class: IP23
Alternator speed: 3000 rpm
Number of poles: 2
Efficiency: 86.4%

Weight: 136 kg
 Width: 466.7 mm
 Length: 548.8 mm
 Height: 460 mm
 Constant speed alternator
 Brushless
 Voltage regulator: AVR

Looking for a product with different features? [Here](#) you can find the full range MECC ALTE and other specialized brands.

Images and technical data are not binding and subject to changes by the manufacturer

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	17 (50Hz) - 20.5 (60Hz)
Continuous power single phase (KW)	15.5 (50Hz) - 18.6 (60Hz)
Maximum power single phase (KVA)	17 (50Hz) - 20.5 (60Hz)
Continuous power single phase (KVA)	15.5 (50Hz) - 18.6 (60Hz)
Maximum power three phase (KW)	21.6 (50Hz) - 26 (60Hz)
Continuous power three phase (KW)	20 (50Hz) - 24 (60Hz)
Maximum power three phase (KVA)	27 (50Hz) - 32.5 (60Hz)
Continuous power three phase (KVA)	25 (50Hz) - 30 (60Hz)
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Poles	2
Single-phase power (KVA)	20.5
Three-phase power (KVA)	32.5
Efficiency (%)	86.4
Protection degree	IP23
Acoustic pressure	74 dB(A) at 7 m
Length (mm)	466
Width (mm)	548.8
Height (mm)	460
Brushes	No
PMG	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	136