



CGM C13000HTE THREE-PHASE GENERATOR 12KVA

Reference: CGM C13000HTE

CGM C13000HTE three-phase generator 12KVA

CGM C13000HTE Three-phase generator 12KVA with HONDA GX630 engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C13000HTE generator is composed of a Made in Italy Linz alternator, self-excited with brushes and with AVR voltage regulator.

The CGM C13000HTE generator is equipped with electric start with 12 V battery but also with manual recoil starter and low fuel consumption, in fact it consumes only 4.8 liters/hour at 75% of the load for an autonomy of up to 3 hours of operation. This CGM C13000HTE is perfect for outdoor use such as hobby use. With optional ATS automatic start panel.

The CGM C13000HTE generator set is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, campgrounds, hobbies, construction sites, etc. The CGM C13000HTE at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM C13000HTE:

Type of phase: Singlephase / Threephase
Maximum singlephase power: 4.4 KVA / 3.5KW
Continuous singlephase power: 4 KVA / 3.2 KW
Maximum threephase power: 13.2 KVA / 10.5 KW
Continuous threephase power: 12 KVA / 9.6 KW
Fuel: Petrol
Voltage: 230/400 V
Frequency: 50 Hz
Engine: HONDA GX630
Engine RPM: 3000 rpm
Starter: Electric
Voltage regulator system: AVR
Consumption: 4.8 Lt/h at 75% of the load
Tank capacity: 15 Lt
Autonomy: 3.1 h at 75% load
Length: 910 mm
Width: 580 mm
Height: 640 mm
Weight: 125 Kg

Discover the full range reserved for [terrestrial generator sets](#) of CGM or other top brands by browsing our catalog to find the one

that best suits your needs.

Images and technical data are not binding.

Technical Sheet

| Phase | Single phase / Three phase |
|-------------------------------------|----------------------------|
| Maximum power single phase (KW) | 3.5 |
| Continuous power single phase (KW) | 3.2 |
| Maximum power single phase (KVA) | |
| Continuous power single phase (KVA) | 4 |
| Maximum power three phase (KW) | |
| Continuous power three phase (KW) | |
| Maximum power three phase (KVA) | 13.2 |
| Continuous power three phase (KVA) | |
| Fuel | Gasoline |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 / 400 |
| Sockets configuration | |
| Engine | HONDA GC160 |
| Emissions Regulations | Stage 5 |
| Engine rpm (rpm) | 3000 |
| Starting system | Elettrico |
| Engine capacity (cm ³) | |
| Number cylinders | 2 |
| Alternator | Made in Italy |
| Poles | 2 |
| Fuel tank capacity (L) | 15 |
| Consumption (L/h) | 4.8 |
| Running time (h) | 3.1 |
| Length (mm) | 910 |

| | |
|---------------------|--------------|
| Width (mm) | 580 |
| Height (mm) | 640 |
| Dry weight (Kg) | |
| Silenced | No |
| Super silenced | No |
| Product type | Generator |
| ATS Switch device | Optional ATS |
| Voltage regulator | AVR |
| Engine manufacturer | Honda |