



PRAMAC WX 3200 ES SINGLE PHASE GENERATOR 2.85 KVA AVR STAGE V

Reference: PR242SXBZ03

PRAMAC WX 3200 ES SINGLE PHASE GENERATOR 2.85 KVA AVR STAGE V

PRAMAC WX 3200 ES is a single-phase generator equipped with a Pramac OHV **StageV** petrol-powered engine, capable of delivering a maximum power of 2,85 KVA **complete with AVR voltage regulator**.

The PRAMAC WX 3200 ES is equipped with sturdy handles and wheels that allow easy portability; like all the PRAMAC WX 3200 ES range, it is a generator that meets a high quality standard and guarantees a high level of reliability.

The strengths of the PRAMAC WX 3200 ES are: the high quality of the components, lightness, compactness, portability and ease of use and also the modern design. The single-phase 2.85 KVA generator is equipped with a manual rope start and electric start.

The PRAMAC WX 3200 ES has been specially developed for camping, caravans, homes, and hobby applications, etc., for this reason it reflects peculiar characteristics and comforts that allow its reliability and comfort in the fields of application.

STAGEV EMISSIONS REGULATION

The generator is equipped with a "mobile" STAGEV motorization, as required by the European Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate matter and nitrogen oxides delivered by the generator into the environment, and ensure a reduction in the environmental impact of 200% compared to standard engines.

The advantages of the AVR voltage regulator

The automatic voltage regulator, or AVR allows the single-phase 2.85 KVA generator to deliver stable energy and therefore be able to connect equipment with delicate electronics such as computers, appliances, smartphones and tablets: the generator is therefore ideal for domestic use, in camping, for hobby and leisure, but also for construction sites and craftsmen.

The AVR voltage regulator and the other quality standard of the alternator with copper windings will provide you with safe and stabilized energy.

Technical Characteristics of the PRAMAC WX 3200 ES

Type of phase: Single-phase
Continuous power: 2.4 KVA / 2.4 KW
Maximum power: 2.85 KVA / 2.85 KW
VAC voltage: 230 V
Frequency (Hz) : 50
Voltage regulator: AVR
Starting panel: Electric / Recoil
Engine: Pramac OHV
Emissions standard: Stage V

Revolutions per minute RPM: 3000
 Fuel supply: Petrol
 Tank capacity: 17 l
 Consumption @ 50% load: 1.04 l / h
 Autonomy @ 50% load: 16.3 h
 Acoustic pressure : 65 dB (A) @ 7m
 Length: 680 mm
 Width: 602 mm
 Height: 523 mm
 Net weight: 49 Kg

Are you looking for a generator with different technical characteristics? [HERE](#) you can find the area dedicated to PRAMAC generators or other specialized brands

Non-binding images and data and may be subject to revisions.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2.8
Continuous power single phase (KW)	2.4
Maximum power single phase (KVA)	2.8
Continuous power single phase (KVA)	2.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	PRAMAC OHV
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Electric and recoil
Cooling	Air
Fuel tank capacity (L)	17
Consumption (L/h)	1.04 at 50% of load
Running time (h)	16.3 at 50% of load
Acoustic pressure	65 dB(A) at 7 m
Length (mm)	680
Width (mm)	602
Height (mm)	523
Dry weight (Kg)	49
Inverter	No
AVR	Yes

Compound	No
Silenced	Yes
Super silenced	No
ATS Switch device	Optional ATS
Voltage regulator	AVR
Video	KhKXnERgwa8
