



PRAMAC S12000 THREE-PHASE Generator set +DPP, AVR

Reference: PD123TH200H

PRAMAC S12000 THREE PHASE DPP AVR.

Introducing the PRAMAC S12000, a state-of-the-art three-phase generator with DPP AVR technology. Designed to deliver consistent and reliable power, this model ensures optimal voltage stability across all operations. The PRAMAC S12000 epitomizes high-end performance coupled with precision engineering, making it an indispensable asset for diverse power needs.

Motor Honda Serie GX.

The image is purely indicative

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	4.48
Continuous power single phase (KW)	4
Maximum power single phase (KVA)	5.6
Continuous power single phase (KVA)	5
Maximum power three phase (KW)	11.1
Continuous power three phase (KW)	9.5
Maximum power three phase (KVA)	13.9
Continuous power three phase (KVA)	11.8
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	
Engine	Honda GX160, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical

Starting system	Elettrico
Engine capacity (cm ³)	
Oil capacity (L)	1.9
Cooling	Air
Poles	2
Fuel tank capacity (L)	24
Consumption (L/h)	4.23 at 75% of the load / 5.63 at 100% of the load
Running time (h)	5.67 at 75% of the load / 4.26 at 100% of the load
Acoustic power	96 dB(A)
Acoustic pressure	72 dB(A) at 7 m
Length (mm)	960
Width (mm)	641
Height (mm)	667
Dry weight (Kg)	
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda