



PRAMAC P3000i SINGLE-PHASE GENERATOR 2.5 KW INVERTER

Reference: PF262SXI000

PRAMAC P3000i SINGLE-PHASE GENERATOR 2.5 KW INVERTER

The PRAMAC P3000i single-phase generator is equipped with an Pramac OHV petrol engine, delivers a power of 2,5 KW and is equipped with **Inverter voltage regulator**.

The PRAMAC P3000i is among the quietest in its class as it has been designed with soundproofing coatings and the exclusive silencer of the exhaust system.

Designed with lightweight materials to enhance portability and ergonomically designed, this portable power generator is extremely easy to lift and carry.

The voltage regulator with inverter technology guarantees you a constant, clean and uninterrupted supply of electricity. In this way, thanks to the inverter, **you can connect your sensitive devices to your generator** (PCs, smartphones, appliances, etc.) in complete safety and without burning them.

PRAMAC P3000i can be connected together by means of a parallel cable that doubles the power. Connected in this way, they can **meet the needs of small structures** such as supplying electricity to ensure the operation of the air conditioner in a camper. Two smaller gensets are easier to handle and transport than a large one, and once in place they can be connected to increase power.

TECHNICAL FEATURES PRAMAC P3000i

Type of phase: Single-phase
Continuous power: 2.3 KVA / 2.3 KW
Maximum power: 2.5 KVA / 2.5 KW
Engine: Pramac OHV
Engine revolutions: 3000 rpm
Emissions regulations: Not emitted
Starting: Tear-off with recoil
Fuel: Petrol
Voltage: 230 V
Frequency: 50 Hz
Sockets panel: 2 x SCHUKO 230V 16A
Voltage regulator: Inverter
Tank capacity: 4 l
Consumption at 75% of the load: 1.14 l / h
Autonomy at 75% of the load: 3.5 h
Acoustic pressure: 61 dB (A) @ 7 m
Length: 565 mm
Width: 339 mm

Height: 467 mm
Dry weight: 27 Kg

Are you looking for a generator with different technical characteristics? [HERE](#) You can find the area dedicated to specialized brand generators.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2.5
Continuous power single phase (KW)	2.3
Maximum power single phase (KVA)	2.5
Continuous power single phase (KVA)	2.3
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A SCHUKO
Engine	OHV
Speed governor	Electronic
Starting system	Pull starter with recoil
Number cylinders	1
Cooling	Air
Fuel tank capacity (L)	4
Consumption (L/h)	1.14 al 75% del carico
Running time (h)	3.5 al 75% del carico
Acoustic power	88 dB(A)
Acoustic pressure	61 dB(A) at 7 m
Length (mm)	565
Width (mm)	339
Height (mm)	467
Dry weight (Kg)	27
Inverter	Yes
Silenced	Yes
Super silenced	Yes
ATS Switch device	No ATS
Voltage regulator	Inverter
Engine manufacturer	PRAMAC