



## WFM SE12000-MTHE AVR

Reference: 04001

### Technical Sheet

|                                    |                         |
|------------------------------------|-------------------------|
| Phase                              | Single phase            |
| Maximum power single phase (KW)    | 3.6                     |
| Maximum power single phase (KVA)   | 4.5                     |
| Fuel                               | Gasoline                |
| Frequency (Hz)                     | 50                      |
| Voltage (V)                        | 230                     |
| Sockets configuration              | 1 x 230V - 1 x 230V CEE |
| Engine                             | Honda GX270             |
| Engine rpm (rpm)                   | 3000                    |
| Ignition                           | Recoil                  |
| Starting system                    | Pull starter            |
| Engine capacity (cm <sup>3</sup> ) | 270                     |
| Number cylinders                   | 1                       |
| Oil capacity (L)                   | 1.1                     |
| Cooling                            | Air                     |
| Fuel tank capacity (L)             | 6                       |
| Consumption (L/h)                  | 2.4 at 100% of the load |
| Running time (h)                   | 2.5 at 100% of the load |
| Acoustic power                     | 95 dB(A)                |
| Acoustic pressure                  | 70 dB(A) at 7 m         |
| Length (mm)                        | 780                     |

---

|                     |        |
|---------------------|--------|
| Width (mm)          | 520    |
| Height (mm)         | 560    |
| Dry weight (Kg)     | 62     |
| Silenced            | No     |
| Super silenced      | No     |
| ATS Switch device   | No ATS |
| Voltage regulator   | AVR    |
| Engine manufacturer | Honda  |

---