



GENSET MG 80 H/A

Reference: MG 80 H/A

Generating Sets from 1 kVA to 2000 kVA with manual or automatic starting.
 Thanks to such a wide range, GenSet is able to present specific solutions in the most diverse fields of application of the genset, both for continuous use and for emergency use in case of interruption of the main power supply.
 All GenSet generating sets strictly comply with EC regulations on safety in use and control of polluting emissions.

The images are purely indicative.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.6
Maximum power single phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x monofase CEE 32 A - 1 x monofase CEE 16 A
Engine	Honda GX 390 OHV
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	390
Number cylinders	1
Cooling	Air
Alternator	Synchronous
Fuel tank capacity (L)	6.5
Consumption (L/h)	2.9
Running time (h)	2.23
Acoustic power	100 dB(A)

Acoustic pressure	75 dB(A) at 7 m
Length (mm)	725
Width (mm)	515
Height (mm)	585
Dry weight (Kg)	93
Silenced	No
Super silenced	No
ATS Switch device	Optional ATS
Voltage regulator	Capacitor / AVR (optional)
Engine manufacturer	Honda