



AGROWATT AWB 4-25 Tractor Generator Single Phase 10 kVA / Three Phase 25 kVA AVR

Reference: 113889

AGROWATT AWB 4-25 SINGLE / THREE-PHASE PTO GENERATOR 25 KVA

The AGROWATT AWB 4-25 single-phase / three-phase PTO generator is capable of delivering 25,0KVA with AVR voltage regulator.

The AGROWATT AWB 4-25 is composed of a frame on which an alternator is placed, which can be connected to the tractor by a special speed increaser on one side, while on the opposite side it is provided with an electric panel with sockets.

The frame of the generator has been projected in order to allow it to work in the best way without being subject to strong vibrations that can compromise its reliability, in addition it is very simple and practical to connect it both to the lifting system and to the power take-off, determining a manageable use without too many troubles.

The AGROWATT AWB 4-25 is driven by means of a cardan connection thanks to the action of the P.T.O. (Power Take Off) of an agricultural tractor through direct coupling to the cardan shaft. The whole is fixed on a sturdy metal frame to protect the alternator and allow for more convenient use.

The AGROWATT AWB 4-25 needs to be connected to a tractor capable of delivering 77 Hp or more for proper operation.

Voltage Regulator AVR

The voltage regulator is indispensable to make the generator work at its best, in fact it needs an electronic control system, an AVR, which guarantees the good working of the machine and of the electric net underneath it.

The purpose of the AVR, in a current generator, is to maintain a stable output. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed current opposes the inductor magnetic field, causing a voltage drop at the alternator output terminals; to compensate the phenomenon, the AVR intervenes automatically increasing the excitation current, until the output returns to the nominal value. If the load is capacitive, the current magnetizes the inductor causing an increase in output voltage, and the AVR intervenes by reducing the excitation current.

TECHNICAL CHARACTERISTICS AGROWATT AWB 4-25

Phase Type: SinglePhase/ThreePhase
Maximum Single-Phase Power: 10 KVA / 8 KW
Maximum Three-Phase Power: 25 KVA / 20 KW
Alternator RPM: 1500 rpm
Tractor Power: 77 Hp
Power Take-Off Speed: 430 rpm
Socket Frame: 1 x 400V 63A - 1 x 230V 32A - 1 x 230V SCHUKO
Voltage: 230 / 400 V
Frequency: 50 Hz

Voltage Regulator: AVR
 Protection Class: IP 23
 Length (mm): 1160
 Width (mm): 640
 Height (mm): 915
 Dry Weight (Kg): 205

Are you looking for a PTO generator with different technical characteristics? [HERE](#) you can find the area dedicated to AGROWATT PTO generators or other brands specializing in the field.

Images and technical data not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	8
Maximum power single phase (KVA)	10
Maximum power three phase (KW)	20
Maximum power three phase (KVA)	25
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 32A 3P+N+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V SCHUKO
Engine rpm (rpm)	1500
Protection degree	IP23
PTO speed (round/min)	430
Minimum tractor output (HP)	77
Transmission ratio	1 : 3.5
Length (mm)	1135
Width (mm)	640
Height (mm)	915
Dry weight (Kg)	205
Brushes	No
Voltage regulator	AVR