



SINCRO FT2 MGR Three Phase Synchronous AC Alternator 18 kVA D-AVR

Reference: FT2 MGR

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

Not binding images and technical data.

Technical Sheet

Phase	Three phase
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Poles	2
Three-phase power (KW)	14.4
Three-phase power (KVA)	18
Efficiency (%)	85.4
Protection degree	IP23
Dry weight (Kg)	67
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Digital AVR