



SINCRO FT4 MBR Three Phase Synchronous AC Alternator 9 kVA D-AVR

Reference: FT4 MBR

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

The image is purely indicative.

Technical Sheet

| | |
|-------------------------|----------------|
| Phase | Three phase |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 / 400 |
| Engine rpm (rpm) | 1500 |
| Poles | 4 |
| Three-phase power (KW) | 7.2 |
| Three-phase power (KVA) | 9 |
| Efficiency (%) | 79 |
| Protection degree | IP23 |
| Dry weight (Kg) | 37 |
| Brushes | Yes |
| Type of alternator | Constant Speed |
| Voltage regulator | Digital AVR |