



GENSET MG 12 I-H/AE - SINGLE-PHASE/THREE-PHASE GENERATOR 11 KVA AVR

Product description:

GENSET MG 12 I-H/AE

The GENSET MG 12 I-H/AE is a single-phase/three-phase 11 KVA petrol generator with electric start and AVR voltage regulator. This generator is also available in the version with automatic panel and remote control.

The GENSET MG 12 I-H/AE also has a low fuel consumption: only 5.5 Lt/h at 75% of the load.

The GENSET MG 12 I-H/AE generator set, thanks to the high quality and efficiency of its components, is ideal for various types of work: from small hobby jobs to large construction sites.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Maximum power single phase (KVA): 4

Maximum power three phase (KW): 8.8

Continuous power three phase (KW): 8

Maximum power three phase (KVA): 11

Continuous power three phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A CEE - 1 x 230V 16A CEE

Engine: Honda GX630, 4 stroke, OHV

Emissions Regulations: Stage 5



Engine rpm (rpm): 3000
Starting system: Electric
Engine capacity (cm³): 688
Number cylinders: 2
Cooling: Air
Alternator: Synchronous
Protection degree: IP23
Motor insulation class: H
Fuel tank capacity (L): 29
Consumption (L/h): 5.5
Running time (h): 5.27
Acoustic power: 98 dB(A)
Acoustic pressure: 73 dB(A) at 7 m
Length (mm): 904
Width (mm): 507
Height (mm): 823
Dry weight (Kg): 148
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Honda