



# GENMAC QUEEN-GAS G60GS-LPG THREE- PHASE GENERATOR 61 KVA LPG GAS - STAMFORD ALTERNATOR

## Product description:

### GENMAC QUEEN-GAS G60GS-LPG

The GENMAC QUEEN-GAS G60GS-LPG is a 61 KVA super-silenced single-phase/three-phase LPG generator set with Stamford alternator and AVR voltage regulator.

Thanks to its LPG gas fuel supply, the GENMAC QUEEN-GAS G60GS-LPG can only consume 26.3 Lt/h at full load and has a low environmental impact, making it one of the best in its class.

The long life and reliability of the GENMAC QUEEN-GAS G60GS-LPG is due to a special control procedure during the various stages of production.

The GENMAC QUEEN-GAS G60GS-LPG is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

Not binding images and technical data.

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 54

Continuous power three phase (KW): 48

Maximum power three phase (KVA): 67

Continuous power three phase (KVA): 61

Fuel: LPG



Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: Terminal box  
Engine: General Motors RMG5700-D51-01  
Emissions Regulations: Stationary Use  
Engine rpm (rpm): 1500  
Speed governor: Electronic  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 5700  
Number cylinders: 8  
Oil capacity (L): 4.7  
Cooling: Water  
Alternator: Stamford S1L2-Y1, self-excited  
Poles: 4  
LPG consumption (L/h): 26.3  
Width (mm): 1056  
Height (mm): 1900  
Dry weight (Kg): 1359  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: General Motors

