

NSM K100 FX - SINGLE PHASE ALTERNATOR 5.5 KVA CAPACITOR

Product description:

NSM K100 FX

The NSM K100 FX is a 5.5 KVA single-phase constant speed alternator with capacitor voltage regulator.
This alternator belongs to the portable category with 2 poles of 3000 rpm.
The versatility of NSM products and their robust design make the industrial series suitable to meet the requirements of industry and the most demanding technological specifications required in various applications.

To couple the NSM K100 FX alternator to a main engine, you can choose between these flanges and discs:
- J609a cone 19
- J609b cone 22
- J609b cone 25.4
- B3/B9 cone 23

Please check the compatibility of the available couplings with your engine before placing your order.
Configuration included in the price: without top cover and without cable connector.

Not binding images and technical data.

Product features:

Phase: Single phase
Maximum power single phase (KW): 5.5

Maximum power single phase (KVA): 5.5
Frequency (Hz): 50
Voltage (V): 230
Engine rpm (rpm): 3000
Poles: 2
Single-phase power (KW): 5.5
Single-phase power (KVA): 5.5
Efficiency (%): 75.5
Protection degree: IP23
Motor insulation class: H
Brushes: No
PMG: No
Product type: Alternator
Type of alternator: Constant Speed
Voltage regulator: Capacitor
Weight (Kg): 23.5