



CGM C7000T

Product price:

1.637,50 € tax excluded

Product description:

Generator CGM C7000T Three-phase 7 KVA

CGM C7000T single/threephase 7 KVA generator set with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C7000T generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C7000T generator set is equipped with manual recoil starter with recoil starter and low fuel consumption, in fact it consumes only 2 litres/hour at 75% of the load. This CGM C7000T generator set is perfect for outdoor use such as hobby use.

The CGM C7000T generator set is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, street installations, camping sites, hobbies, construction sites, etc.. The CGM C7000T at 3000 rpm is only suitable for emergency use. We do not recommend use for more than 6 consecutive hours and more than 500 hours per year.

Technical characteristics of the CGM C7000T:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 2.6 KVA / 2 KW

Continuous singlephase power: 2.3 KVA / 1.8 KW

Maximum threephase power: 7.7 KVA / 6.1 KW

Continuous threephase power: 7 KVA / 5.6 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: HONDA GX390

Engine rpm: 3000 rpm

Starting: Manual



Voltage regulator system: AVR
Consumption: 2 Lt / h at 75% of the load
Tank capacity: 6.1 Lt
Autonomy: 3 h at 75% of the load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 75 Kg

Discover the full range of generators from CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 2
Continuous power single phase (KW): 1.8
Maximum power single phase (KVA): 2.6
Continuous power single phase (KVA): 2.3
Maximum power three phase (KW): 6.1
Continuous power three phase (KW): 5.6
Maximum power three phase (KVA): 7.7
Continuous power three phase (KVA): 7
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE
Engine: Honda GX390
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Manual
Engine capacity (cm³): 389
Number cylinders: 1
Alternator: Made in Italy
Poles: 2
Fuel tank capacity (L): 6.1
Consumption (L/h): 2
Running time (h): 3
Length (mm): 780





Width (mm): 510
Height (mm): 500
Dry weight (Kg): 75
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda