



# CGM C11000T

**Product price:**

**2,422.50 € tax excluded**

## Product description:

### **CGM C11000T Three-phase generator 10 KVA**

CGM C11000T Three-phase generator 10 KVA with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C11000T is composed of a Made in Italy alternator by Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C11000T generator set is equipped with manual recoil start and with a low fuel consumption, in fact it consumes only 2,2 liters/hour at 75% of the load for an autonomy up to 3 hours of operation. This generating set CGM C11000T is perfect for outdoor use as for example for hobby use.

The CGM C11000T is part of the CLASSIC series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites etc.. The CGM C11000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

## Technical features of CGM C11000T:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 3.6 KVA / 3 KW

Continuous singlephase power: 3.3 KVA / 2.6 KW

Maximum threephase power: 11 KVA / 8.8 KW

Continuous threephase power: 10 KVA / 8 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: BRIGGS & STRATTON 16HP

; Engine revolutions: 3000 rpm

Starting: Manual

Voltage regulator system: AVR



Consumption: 3.8 Lt / h at 75% of the load

Capacity tank: 8.5 Lt

Autonomy: 2.2 h at 75% of the load

Length: 910 mm

Width: 580 mm

Height: 640 mm

Weight: 97 Kg

Discover the full range reserved for [generator](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

#### **Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 3

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA):

Continuous power single phase (KVA): 3.3

Maximum power three phase (KW): 8.8

Continuous power three phase (KW): 8

Maximum power three phase (KVA): 11

Continuous power three phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE

Engine: Briggs&Stratton

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Manuale

Engine capacity (cm<sup>3</sup>): 480

Number cylinders: 2



Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L):

Consumption (L/h): 3.8

Running time (h): 2.2

Length (mm): 910

Width (mm): 580

Height (mm): 64

Dry weight (Kg): 97

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton

