



CGM CX7000T

Product price:

1.650,00 € tax excluded

Product description:

Generator Three-phase CGM CX7000T 7KVA AVR

Generator CGM CX7000T 7KVA three-phase with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with sturdy rain cover and vibration dampers. The CGM CX7000T generator set is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with an AVR regulator. The AVR regulator allows to stabilize the voltage and does not ruin the connected sensitive devices. The CGM CX7000T generator set is equipped with manual recoil start and low fuel consumption, in fact it consumes only 2 liters/hour at 75% load. This CX7000T generator set is perfect for outdoor use such as hobby use. The CGM CX7000T generator is part of the DELUXE series and is easily adaptable to various uses such as homes, mobile homes, camping, hobbies, construction sites, etc.. The CX7000T generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical characteristics of CGM CX7000T generator:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 2.5 KVA / 2 KW

Continuous singlephase power: 2.3 KVA / 1.8 KW

Maximum threephase power: 7.7 KVA / 6.1 KW

Continuous threephase power: 7 KVA / 5.6 KW

Fuel: Petrol

Voltage: 230 V / 400 V

Frequency: 50 Hz

Motor: HONDA GX390

Engine revolutions: 3000 rpm

Starting: Manual

Voltage regulator system: AVR



Consumption: 2 Lt / h at 75% of load

Tank capacity: 15 Lt

Autonomy: 7.5 h at 75% of the load

Length: 825 mm

Width: 550 mm

Height: 530 mm

Weight: 76 Kg

Discover the entire range reserved for generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2

Continuous power single phase (KW): 2.3

Maximum power single phase (KVA): 2.5

Continuous power single phase (KVA): 1.8

Maximum power three phase (KW): 6.1

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 7.7

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO

Engine: Honda GX390

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Manual

Engine capacity (cm³): 389

Number cylinders: 1

Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 15

Consumption (L/h): 2

Running time (h): 7.5

Length (mm): 825





Width (mm): 550
Height (mm): 530
Dry weight (Kg): 76
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda