



# MARELLIMOTORI ALTERNATOR 275KVA MXB-E 250 LA4

## Product description:

MARELLIMOTORI MXB-E 250LA4 ALTERNATOR 275KVA THREEPHASE

**MARELLIMOTORI** MXB-E 250LA4 is a **Alternator** with a power of 275KVA 220KW, this unit has a self-exciting and self-regulating Brushless operation.

The MXB-E 250LA4 is designed to operate at frequency 50 or 60 HZ, the possibility to work on these two frequencies makes it possible to apply it for any service voltage increasing its versatility, for correct operation. For correct operation it is only necessary to check that the settings are correct for the intended use.

MarelliMotori is supplied with 12 terminals (7 terminals), with which it is normally possible to connect both series and parallel star alternator. According to the needs, it is possible to switch from one connection to another, bearing in mind that the connection of the AVR must necessarily be checked.

MXB-E 250LA4 threephase can be used as singlephase as required. MarelliMotori MXB-E 250LA4 is equipped with AVR type M00FA122A - MARK VX, suitable for synchronous generators of MARELLIMOTORI construction. The regulator is suitable for operation both on threephase generators and on single-phase generators, allowing a fast, precise and reliable set-up.

The M00FA122A is an electronic board designed by MarelliMotori, it is protected by a polyurethane resin that protects the device from humidity, dust, aggressive environments. In addition, the AVR is equipped with an internal fuse protection system (5 A, 500 V), which in case of failures or overloads, intervenes and protects the unit in order to make the system safer to place. The M00FA122A serves to make the current stable so as not to ruin the equipment that connects us, especially electronic equipment such as computers or smartphones.

The AVR designed by MarelliMotori is internally equipped with a radio noise filter, which allows to contain radio noise emitted by MarelliMotori generators within the limits set by the European



regulations for industrial environments

Each engine has a type of connection to be connected to the alternator so you must pay attention to this aspect; a model can also have 15 to 20 different forms of construction!

We always recommend to check with the help of the technical data sheets the construction form of the desired alternator.

Select the alternator that reflects the **technical specifications you require**, visit our dedicated section to understand how.

#### TECHNICAL FEATURES OF THE ALTERNATOR 275KVA THREEPHASE MXB-E 250LA4

Phase type: Threephase

Maximum power 50Hz: 275.0 KVA

Maximum power 50Hz: 220.0 KW

Maximum power 60Hz: 344.0 KVA

Maximum power 60Hz: 275. 0 KW

Frequency: 50 - 60Hz

Voltage: 400V / 480V

Protection degree: IP23

A alternator speed: 1500 / 1800 rpm

Number of poles: 4

Yield: 92.9%

Weight: 780.0Kg

Constant speed

AVR

Are you looking for a product with different characteristics? [HERE](#) you can find the entire range **MARELLIMOTORI** and other specialized brands.

Images and technical data not binding and subject to change by the manufacturer

#### Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 220

Maximum power three phase (KVA): 275

Frequency (Hz): 50 / 60

Voltage (V): 400

Engine rpm (rpm): 1500

Poles: 4

Efficiency (%): 92.9

Protection degree: IP23





Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 780

