

# EGM RP6000-SE GENERATOR 5,5KW



**Product price:**

**782,25 € tax excluded**

## **Product description:**

EGM RP6000-SE SINGLEPHASE GENERATOR 5,5KW

The generator EGM RP6000-SE singlephase is equipped with a gasoline engine capable of delivering 5,5KW power with AVR voltage regulator.

The EGM RP6000-SE generator provides reliable power for home, work and leisure environments Safe powering of home appliances and other electronic devices Outdoor party solution.

The EGM RP6000-SE generator is easy to install and operate, as simple as starting and stopping with clear and intuitive controls (pull start) Auto power off for low oil level Durable chassis.

The 5,5KW singlephase generator is equipped with bolted, heavy duty wheels and hinged handle make it a robust and easy to transport. The recessed sockets with snap-on safety covers make it more secure.

The EGM RP6000-SE generator has a practical double-curved handle, which can be folded down for easy mobility and storage. EGM RP6000-SE has an all-steel construction and a large metal tank with fill indicator. The generator guarantees an efficient and silent operation thanks to the OHV engine that allows to deliver a maximum power of 5,5KW.

The AVR is indispensable to make the generator work at its best, it all needs an electronic control system, an AVR, which guarantees the good functioning of the machine and of the electrical network behind it.

The purpose of the AVR, in a current generator, is to keep the output stable. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed shift current counteracts the inductor magnetic field, causing a voltage drop at the alternator output terminals; to compensate for this phenomenon, the AVR intervenes

automatically by increasing the excitation current, until the output returns to the nominal value.

## TECHNICAL CHARACTERISTICS OF THE GENERATOR EGM RP6000-SE 5,5KW

Phase Type: Single-phase  
Single-phase Continuous Output: 5 KVA / 5 KW  
Single-phase Maximum Output: 5.5 KVA / 5.5 KW  
VAC Voltage: 230 V  
Frequency (Hz): 50  
Voltage Regulator: AVR  
Starter Panel: Manual with recoil starter  
RPM: 3000  
Supply By: Gasoline  
Tank Capacity: 25 l  
Consumption: 1.92 l/h @ 50 % of load  
Autonomy: 13 h @ 50 % of load  
Sound pressure: 97 dB(A) @ 7m  
Length: 700 mm  
Width: 526 mm  
Height: 580 mm  
Net weight: 90 Kg

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 5.5  
Continuous power single phase (KW): 5  
Maximum power single phase (KVA): 5.5  
Continuous power single phase (KVA): 5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 x 230V 16A 2P+T CE - 1 x 230V 32A 2P+T CE  
Emissions Regulations: Stationary Use  
Engine rpm (rpm): 3000  
Speed governor: Mechanical  
Starting system: Manual  
Cooling: Air

Poles: 2

Fuel tank capacity (L): 25

Consumption (L/h): 1.92 l/h @ 50 %

Running time (h): 13 h @ 50 %

Acoustic pressure: 97 dB (A) @ 7 m

Length (mm): 700

Width (mm): 526

Height (mm): 580

Dry weight (Kg): 90

Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: AVR