



CUMMINS C66 D5e THREE-PHASED DIESEL POWER GENERATOR 66KVA SILENCED

Product price:

13,958.00 € tax excluded

Product description:

CUMMINS C66 D5 THREE-PHASE 66KVA SILENCED DIESEL GENERATOR SET

The special feature of Cummins generator sets is that they are manufactured using the engine, alternator, electrical control panel and other components built by Cummins Inc. companies.

Key features CUMMINS C66 D5

Cooling system - Standard system with integrated radiator, designed and tested for ambient temperatures.

Control System - PowerStart control, microprocessor based genset with a monitoring and control system providing a simple interface to the genset, manual and remote start/stop control and shutdown fault indication.

Silenced enclosure - High weather protection and great soundproofing.

Heavy-duty Cummins industrial 4-stroke diesel engine provides reliable, low-emission power with fast response time to load changes.

Optional Excitation Boost System (EBS) - Provides improved starting to minimise short circuits and engine failures.

Alternator - Several alternator sizes offer selectable engine starting capability with low reactance; low distortion waveform even with non-linear loads and fault and short circuit compensation capability.

On-board accessories



Lead batteries on board the unit (supplied without liquid); Mechanical radiator for ambient temperature to + 50°C.

Sheet steel base frame with tank welded inside, vibration dampers.

Soundproof enclosure complete with residential muffler according to European standards, made of 2 mm thick sheet steel, treated and painted for outdoor exposure; Engine coolant pre-heating system.

Automatic electrical panel (ATS excluded)

4-pole magneto-thermal protection switch

On-board control panel for generating set - PCC0500

Main control functions

- Digital measurement of AC output.
- Digital display of alarm and status messages.
- Generator set monitoring: Displays the status of all critical functions of the generator set engine and alternator.
- Advanced service and maintenance functions.

Controls and adjustments

- OFF/START/AUTO buttons
- Emergency stop "STOP" button

Used to stop the genset immediately and easily in the event of an emergency.

- Menu Settings for voltage, frequency, starting and stopping delay

Customer interface

- Communication protocol: Modbus RS 485 or RS 232
- 4 configurable input contacts
- 2 configurable output relays



Product features:

Phase: Single phase / Three phase Maximum power three phase (KW): 66 Continuous power three phase (KW): 48 Maximum power three phase (KVA): 60 Continuous power three phase (KVA): 53

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230 / 400

Sockets configuration: Terminal box

Engine: 4 stroke

Emissions Regulations: Stage 3A

Engine rpm (rpm): 1500 Speed governor: Mechanical Starting system: Electric Number cylinders: 4

Cylinders' position: In line Cooling: Coolant Liquid

Alternator: Synchronous, brushless

Poles: 4

Bore x stroke (mm): 91.4x127

Fuel tank capacity (L):

Consumption (L/h): 12 at 75% of the load / 16 at 100% of the load

Running time (h): 12.5 at 75% of the load

Length (mm): 2270 Width (mm): 975 Height (mm): 1920 Dry weight (Kg): 1511

Silenced: Yes

Super silenced: Yes

Brushes: No

Product type: Generator Control unit: PowerStart 600 ATS Switch device: Optional

Type of alternator: Constant Speed

Voltage regulator: AVR

Engine manufacturer: Cummins

Precision of voltage regulation: ± 2,5%

