



# GENERATOR SINGLE-PHASE / THREE-PHASE STAGEV 19,2KVA AVR

Product price:

**6.812,50 € tax excluded**

## Product description:

### GENERATOR SINGLE-PHASE / THREE-PHASE STAGEV 19,2KVA AVR

Generator single-phase / three-phase of 19,2 KVA with BRIGGS & STRATTON engine powered by STAGEV Gasoline at 3000 rpm, compact and easy to use.

The generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The generator is equipped with electric start with battery that allows a practical and fast use even when cold. The generator has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The generator is not supplied with feet as these are supplied separately.

The generator is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 RPM, with BRIGGS & STRATTON engine with electric start with key and battery.

## STAGEV EMISSIONS REGULATION

The generator is equipped with a "mobile" STAGEV motorization, as required by the European Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate matter and nitrogen oxides delivered by the generator into the environment, and ensure a reduction in the environmental impact of 200% compared to standard engines.

## TECHNICAL FEATURES

Phase Type: Single-phase / Three-phase

Singlephase Continuous Power: 5.8 KVA / 4.6 KW

Singlephase Maximum Power: 6.4 KVA / 5.1 KW

Threephase Continuous Power: 17.5 KVA / 14 KW



Threephase Maximum Power: 19.2 KVA / 15.3 KW

Power Factor cos  $\phi$ : 0.8

VAC voltage: 230 / 400 V

Frequency (Hz): 50

Voltage regulator: AVR

Start framework: Manual / Automatic

Engine: BRIGGS & STRATTON 31HP

RPM: 3000

Power supply: Gasoline

Emissions standard: STAGE V

Fuel tank capacity: 60 l

Fuel consumption @ 75 % load: 6.5 l/h

Autonomy @ 75 % load: 9.2 h

Sound pressure: 72 dB(A) @ 7m

Length: 1200 mm

Width: 730 mm

Height: 930 mm

Net weight: 280 Kg

Manual electric panel with:

n. 1 CEE 16A 3P 230V socket

n. 1 CEE 32A 5P 400V socket

General switch

connector for ATS

hour counter

Discover the full range of current generator on our catalog to find the one that best suits your needs.

Pictures and technical data not binding.

### Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 5.1

Continuous power single phase (KW): 4.6

Maximum power single phase (KVA): 6.4

Continuous power single phase (KVA): 5.6

Maximum power three phase (KW): 15.3

Continuous power three phase (KW): 14

Maximum power three phase (KVA): 19.2

Continuous power three phase (KVA): 17.5

Fuel: Gasoline





---

Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 230V 63A 3P CEE - 1 x 230V 16A 3P - 1 x 230V SCHUKO  
Engine: BRIGGS & STRATTON 31HP  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Manual / Automatic  
Engine capacity (cm<sup>3</sup>): 896  
Number cylinders: 2  
Cooling: Air  
Alternator: NSM, made in Italy  
Fuel tank capacity (L): 60  
Consumption (L/h): 6.5 @ 75 % del carico  
Running time (h): 9.2 @ 75 % del carico  
Length (mm): 1200  
Width (mm): 730  
Height (mm): 930  
Dry weight (Kg): 280  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Briggs&Stratton  
Video: MKDdx7hAnHc

