



PRAMAC ES4000 SINGLE PHASE AVR

Product price:

870,00 € tax excluded

Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated.
Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase
Maximum power single phase (KW): 3.1
Continuous power single phase (KW): 2.6
Maximum power single phase (KVA): 3.4
Continuous power single phase (KVA): 2.9
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230





Sockets configuration: 2 x 230V 16A IP54 SCHUKO
Engine: Honda GX200, naturally aspirated
Engine rpm (rpm): 3000
Speed governor: Mechanical
Ignition: Recoil
Starting system: Pull starter
Engine capacity (cm³): 196
Oil capacity (L): 0.6
Cooling: Air
Alternator: With brushes
Poles: 2
Fuel tank capacity (L): 11
Consumption (L/h): 1.2 at 75% of the load / 1.6 at 100% of the load
Running time (h): 9.3 at 75% of the load / 7 at 100% of the load
Acoustic power: 95 dB(A)
Acoustic pressure: 67 dB(A) at 7 m
Length (mm): 623
Width (mm): 409
Height (mm): 500
Dry weight (Kg): 43
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda

