



Shop name



PRAMAC ES8000 SINGLE-PHASE PETROL Generator, AVR

Product price:

1,756.58 € tax excluded

Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated. Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase

Maximum power single phase (KW): 6.4

Continuous power single phase (KW): 5.5

Maximum power single phase (KVA): 7.2

Continuous power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230



Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44
Engine: Honda GX390 Recoil, naturally aspirated
Engine rpm (rpm): 3000
Speed governor: Mechanical
Ignition: Recoil
Starting system: Pull starter
Engine capacity (cm³): 389
Oil capacity (L): 1.1
Cooling: Air
Alternator: With brushes
Poles: 2
Fuel tank capacity (L): 11
Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load
Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load
Acoustic power: 97 dB(A)
Acoustic pressure: 69 dB(A) at 7 m
Length (mm): 729
Width (mm): 500
Height (mm): 536
Dry weight (Kg): 73
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda