



PRAMAC S12000 SINGLE-PHASE Generator set + DPP, AVR

Product price:

3,731.93 € tax excluded

Product description:

PRAMAC S12000 Single-Phase Generator 10.7 kW DPP AVR

PRAMAC S12000 Single-phase generator, 10.7 kW, with a gasoline engine running at 3000 rpm. The PRAMAC S12000 generator is equipped with an electric starter but also with a recoil starter for manual recoil starting. The alternator of the PRAMAC S12000 generator is equipped with an **AVR** voltage regulator. The Honda petrol engine makes the S12000 DPP AVR generator **very reliable** as it has been built and designed using top-quality materials.

Thanks to its very low weight and **compact dimensions** it is easy to transport where you need it most. The PRAMAC S12000 DPP AVR single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC S12000 Single-phase DPP AVR generator:

Maximum power single-phase: 10.7 KW

Continuous use power single-phase: 9.1 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX630

Starting: Electric

Consumption: 5.63 Lt/h at 100% of load

Length: 960 mm

Width: 641 mm

Height: 667 mm

Weight: 162 kg

AVR

CONTROL PANEL

Controls:

- Ignition key: OFF - ON - START



- Choke button
- Connector (predisposition for remote control via AMF accessories automatic panel; RSS radio remote control)

Instrumentation:

- Voltmeter
- Hour meter

Protections:

- Differential protection
- Circuit breaker protections
- Oil Guard (low oil level)

Sockets:

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 16A IP44
- N.1 2P+T CEE 230V 32A IP44

The PRAMAC S12000 generator is a professional petrol generator developed by Pramac with the features and equipment necessary to obtain a superior class product. The PRAMAC S12000 generator is characterized by a powerful petrol-powered alternator, protected by a sturdy tubular frame, steel side protection covers, oversized fuel tank, low oil level protection and pre-installed transport kit. The S12000 generator is designed to satisfy long-lasting professional and intensive applications. If you are looking for a generator like the S12000 DPP AVR single-phase generator, we recommend browsing our catalogue of [terrestrial generators](#) to find the one that best suits your needs. Images and data Non-binding technical advice.

Product features:

- Phase: Single phase
 - Maximum power single phase (KW): 10.7
 - Continuous power single phase (KW): 9.1
 - Maximum power single phase (KVA): 11.9
 - Continuous power single phase (KVA): 10
 - Fuel: Gasoline
 - Frequency (Hz): 50
 - Voltage (V): 230
 - Engine: Honda GX630
 - Engine rpm (rpm): 3000
 - Speed governor: Mechanical
 - Starting system: Elettrico
 - Oil capacity (L): 1.9
 - Cooling: Air
-



Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 4.23 at 75% of the load / 5.63 at 100% of the load

Running time (h): 5.67 at 75% of the load / 4.26 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 68 dB(A) at 7 m

Length (mm): 960

Width (mm): 641

Height (mm): 667

Dry weight (Kg): 162

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda

