



PRAMAC P12000 Generator Set Single-phase Three-phase 11.1KW Super- silent STAGE V

Product price:

4,011.82 € tax excluded

Product description:

Generator set PRAMAC P12000 Single/three phase 11,1KW Supersilenced AVR Stage V

PRAMAC P12000 Genset STAGE V single/three-phase 11.1KW genset with petrol-powered engine at 3000 rpm. The PRAMAC P12000 genset is equipped with an electric starter. The alternator of the PRAMAC P12000 genset is with AVR voltage regulator. The Honda petrol engine makes the P12000 AVR genset very reliable as it is built and designed using top quality materials.

Thanks to its enclosure, this genset is supersilenced. The PRAMAC AVR single/three-phase genset is suitable for outdoor use in small construction sites or for small outdoor jobs.

The PRAMAC P12000 can be chosen with or without AVR

Technical characteristics of the PRAMAC P12000 single/three-phase AVR STAGE V generator set STAGE V:

Maximum power Single-phase: 3.68 KW

Single-phase continuous power: 3.2 KW

Maximum power three-phase: 11.1 KW

Three-phase continuous use power: 9.5 KW

[50HZ] EXHAUST GAS EMISSION LEVEL: Stage V

Fuel: Petrol

Voltage: 230 V / 400 V

Frequency: 50 Hz

Engine: Honda GX630



Starter: Electric
Consumption: 5.63 Lt/h at 100% load
Length: 990 mm
Width: 602 mm
Height: 826 mm
Weight: 188 Kg
AVR

CONTROL PANEL

Controls:

- Start key: OFF - ON - START
- CONNECTOR (provision for remote control via AMF automatic panel accessories; RSS radio remote control)

Instrumentation (DGT)

- Voltmeter
- Frequency meter
- Hour meter

Protections:

- Magnetothermal protection
- Differential Protection (DPP)
- Low oil level protection

Sockets:

- N.1 SCHUKO 230V 16A IP54
- N.2 2P+T CEE 230V 16A IP44
- N.1 3P+N+T CEE 400V 16A IP44

The PRAMAC P12000 STAGE V power generator is a professional petrol-powered generator set developed by Pramac with features and equipment necessary for a top-class product. The PRAMAC P12000 current generator with its extremely quiet operation is the ideal generator for use in residential areas or outside working hours.

The PRAMAC P12000 genset is equipped with a reliable petrol engine, first-class components and complete instrumentation.

If you are looking for a genset such as the P12000 AVR single/three phase PRAMAC genset then we recommend that you browse through our catalogue of land-based [PRAMAC gensets](#) to find the one that is closest to your needs.

Non-binding images and technical data.



Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 11.1

Continuous power three phase (KW): 9.5

Maximum power three phase (KVA): 13.9

Continuous power three phase (KVA): 11.8

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration:

Engine: Honda GX630, naturally aspirated

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Elettrico

Engine capacity (cm³):

Oil capacity (L): 1.9

Cooling: Air

Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 4.23 at 75% of the load / 5.63 at 100% of the load

Running time (h): 5.67 at 75% of the load / 4.26 at 100% of the load

Acoustic power: 89 dB(A)

Acoustic pressure: 61 dB(A) at 7 m

Length (mm): 990

Width (mm): 602

Height (mm): 826

Dry weight (Kg):

Silenced: Yes

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR (optional)

Engine manufacturer: Honda

