



PRAMAC E8000 SINGLE-PHASE

Product price:

1,350.56 € tax excluded

Product description:

PRAMAC E8000 Single-phase 6.4 KW generator set

PRAMAC E8000 single-phase 6.4 KW generator set with Honda engine at 3000 rpm in open version. The PRAMAC E8000 single-phase generator set is equipped with a recoil starter with self-winding. The single-phase alternator of the PRAMAC E8000 generator set is brushless with a capacitor voltage regulator. The Honda engine makes this generator set **very reliable** as it is built and designed with high-quality materials.

Thanks to its frame, low weight and **compact dimensions** it is easy to transport where you need energy. The PRAMAC E8000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC E8000 single-phase generator:

Maximum power Single-phase: 6.4 KW

Continuous use power Single-phase: 5.5 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX390 Recoil

Starting: Recoil

Consumption: 2.9 l/t/h at 100% load

Length: 750 mm

Length: 750 mm
Width: 578 mm

Width: 578 mm

Height: 5'3" in
Weight: 72 Kgs

CONTROL PANEL

CONTROLS

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap

**Standard protections:**

- Thermal protection
- Oil Guard (low oil level)

Sockets:

N.1 SCHUKO 230V 16A IP54
N.1 2P+T CEE 230V 32A IP44

The PRAMAC E8000 generator is a petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC E8000 generator is ideal for intense applications and is characterised by a robust structure with a load-bearing tubular frame, which simplifies both use and maintenance operations.

The E8000 generator is the essential generator to satisfy professional applications.

If you are looking for a generator like the PRAMAC E8000 single-phase generator, then we recommend that you browse our catalogue of [terrestrial generators](#) to find the one that best meets your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase

Maximum power single phase (KW): 6.4

Continuous power single phase (KW): 5.5

Maximum power single phase (KVA): 7.2

Continuous power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44

Engine: Honda GX390 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 389

Oil capacity (L): 1.1

Cooling: Air

Poles: 2

Fuel tank capacity (L): 6.1

Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load

Running time (h): 2.9 at 75% of the load / 2.1 at 100% of the load



Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 750

Width (mm): 578

Height (mm): 531

Dry weight (Kg): 72

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Capacitor

Engine manufacturer: Honda

