



PRAMAC ES4000 SINGLE-PHASE PETROL

Product price:

910.46 € tax excluded

Product description:

PRAMAC ES4000 Single-phase generator set 3.1 KW

PRAMAC ES4000 single-phase generator set 3.1 KW with petrol-powered engine at 3000 rpm. The PRAMAC ES4000 generator set is equipped with manual recoil starter with self-winding. The PRAMAC ES4000 generator set alternator is brushless and with voltage regulator with capacitor. The Honda petrol engine makes the ES4000 generator set **very reliable** as it has been built and designed using top quality materials.

Thanks to its very low weight and its **compact dimensions** it is convenient to transport where you need it most. The PRAMAC ES4000 single-phase generator is suitable for outdoor use on small construction sites or for small outdoor jobs for hobby use.

Technical characteristics of the PRAMAC ES4000 generator:

Maximum power Single-phase: 3.1 KW

Continuous use power Single-phase: 2.6 KW

Fuel: Petrol

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GX200

Starting: Recoil

Consumption: 1.6 Lt/h at 100% of load

Length: 623 mm

Width: 409 mm

Height: 500 mm

Weight: 43 Kg

CONTROL PANEL

Controls:

- Switch: OFF - ON
- Ignition: Self-winding
- Fuel tap

**Standard protections:**

- Thermal protection
- Oil Guard (low oil level)

Protections:

- Thermal protection
- Oil Guard (low oil level)

Sockets:

N.2 SCHUKO 230V 16A IP54

The PRAMAC generator ES4000 is a single-phase petrol generator developed by Pramac to guarantee a high level of quality and performance at an attractive price. The PRAMAC ES4000 generator is built with a sturdy structure with a load-bearing tubular frame and adequate steel sheet protections with a built-in oversized tank.

The ES4000 generator is designed to satisfy long-lasting professional and intensive applications.

If you are looking for a generator like the ES4000 single-phase generator then we recommend you browse our catalogue of [gruppi elettrogeni-terrestri](#) to find the one that best suits your needs.

Images and technical data are not binding. Please always consult the technical data sheet issued by the manufacturer. Manel Service does not assume responsibility for any changes made by the manufacturer.

Product features:

Phase: Single phase

Maximum power single phase (KW): 3.1

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA): 3.4

Continuous power single phase (KVA): 2.9

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: Honda GX200, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 196

Oil capacity (L): 0.6



Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 1.2 at 75% of the load / 1.6 at 100% of the load

Running time (h): 9.3 at 75% of the load / 7 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 67 dB(A) at 7 m

Length (mm): 623

Width (mm): 409

Height (mm): 500

Dry weight (Kg): 43

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Capacitor

Engine manufacturer: Honda

