



# PRAMAC ES8000 THREE-PHASE PETROL GENERATOR

**Product price:**

**1,795.18 € tax excluded**

## Product description:

Motore benzina Honda Serie GX. Raffreddamento ad aria. Protezione Oil Guard. Avviamento a strappo. Robusta struttura con telaio tubolare portante. Prese su cuffia con protezioni termiche. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.96

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.7

Maximum power three phase (KW): 6.6

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8.3

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44

Engine: Honda GX390 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical



Ignition: Recoil  
Starting system: Pull starter  
Engine capacity (cm<sup>3</sup>): 389  
Oil capacity (L): 1.1  
Cooling: Air  
Alternator: With brushes  
Poles: 2  
Fuel tank capacity (L): 11  
Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load  
Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load  
Acoustic power: 97 dB(A)  
Acoustic pressure: 69 dB(A) at 7 m  
Length (mm): 729  
Width (mm): 500  
Height (mm): 536  
Dry weight (Kg): 81  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: Compound  
Engine manufacturer: Honda

